



## AC Input Fuse Ratings for all Audio Note™ Products

All fuses are "Anti-Surge" unless otherwise stated.

T/D = Time Delay

All fuses are 5 x 20mm Time Delay type, or Bussmann type GDC  
HT fuses are located internally and should only be replaced by a qualified service technician.

Product	Fuse ratings for:		HT Inside
	240V	120V	
P3	1.6A	2A	
Meishu Line	1.6A	2A	
Meishu Phono	1.6A	2A	
OTO Line	1.25A	2A	
OTO Phono	1.25A	2A	
OTO Line SE	1.25A	2A	
OTO Phono SE	1.25A	2A	
Quest	1.25A	2A	400mA
Conquest	1.25A	2A	400mA
Kageki	1.25A	2A	400mA
Baransu	1.25A	2A	400mA
Neiro	1.25A	2A	400mA
Shinri	1.25A	2A	400mA
Kassai	1.25A	2A	400mA
Kegon	1.25A	2A	400mA
Conqueror	1.25A	2A	400mA
P-Zero	500mA T/D	1A	
CDT-Zero	500mA T/D	500mA	
CDT-One	500mA T/D	500mA	
CDT-Two	500mA T/D	500mA	
M-Zero	500mA T/D	500mA	
M-One	500mA T/D	500mA	
RIAA-Zero	500mA T/D	500mA	
DAC-Zero	500mA T/D	500mA	
DAC-One	500mA T/D	500mA	
DAC-One Sig	500mA T/D	500mA	
M10	800mA	1.25A	
CD 1, 2, &3	500mA	1A	
M1 Line	250mA	500mA	
M1 RIAA	250mA	500mA	
M1 Phono	500mA	1A	
M2 Line	800mA	1.25A	
M2 RIAA	800mA	1.25A	
M2 Phono	1.25A	1.25A	

M8 Line	2 x 500mA	2 x 1.6A
M8 Phono	2 x 1.25A	2 x 1.6A
M6 Line	2 x 1.25A	2 x 1.6A
M6 Line - V2	2 x 800mA	2 x 1.6A
M6 Phono	2 x 1.25A	2 x 1.6A
M6 Phono - V2	2 x 800mA	2 x 1.6A
M5 Line	2 x 1.25A	2 x 1.6A
M3 Line	2 x 1.25A	2 x 1.6A
M3 Line - V2	2 x 800mA	2 x 1.6A
M3 Phono	2 x 1.25A	2 x 1.6A
M3 Line Remote	2 x 800mA	2 x 1.6A
DAC 1	500mA	800mA
DAC 2	800mA	1.6A
DAC 3	800mA	1.6A
DAC 4	800mA	1.6A
DAC 4 Bal - V2	2 x 800mA	2 x 800mA
DAC 5	2 x 1A	2 x 1.6A
P1	1.25A	1.6A
P1 SE	1.25A	1.6A
P2	1.25A	1.6A
P2 SE	1.25A	1.6A
SORO Line	1.25A	2A
SORO Line SE	1.6A	2A
SORO Phono SE	1.6A	2A